

- Accessories
- Accessoires
- Accesorios
- Acessórios

DRX 100 - DRX 250

1 **TRIPPED**

2

3

27141

27142

27140

Only one UVR is permitted!

TRIPPED

27160...68

D1 D2
U-
Undervoltage Release UVR

C1 C2
Shunt Trip ST

27150...55

Cable: 2,5 mm²
14 AWG
4 mm
(0.16")
1 Nm
8.8 lb-in

TRIPPED

IN TRIPPED POSITION	
27141	<p>54 — 51 Alarm switch (switchover)</p> <p>52 — 51</p>
27142	<p>14 — 11 Auxiliary switch + Alarm switch (switchover)</p> <p>12 — 11</p> <p>54 — 51</p> <p>52 — 51</p>
27140	<p>14 — 11 Auxiliary switch</p> <p>12 — 11</p>

N° 4 cable 2,5 mm² # 14 AWG

N° 2 cable 2,5 mm² # 14 AWG

N° 3 cable 1,5 mm² # 16 AWG

N° 6 cable 0,35 mm²

CRACK

FITTING

1

CLICK

2

REMOVING

1

2

3

**DRX 100 < 50A = 27170 (3P)
27172 (4P)**
**DRX 100 > 50A = 27171 (3P)
27173(4P)**

DRX < 50A

Flexible	2,5 → 10 mm ² #14
or	#8 AWG
Solid	2,5 → 16 mm ² #14
or	#6 AWG

DRX > 50A

Flexible	10 → 35 mm ² #8
or	#3/2 AWG
Solid	10 → 50 mm ² #8
or	#1/0 AWG

2,5 to 4 mm² #14 to #10 AWG flexible cables: connection via crimped end-barrels

DRX 100 < 50A = 2 Nm /18 lb-in.
DRX 100 > 50A = 3 Nm /27 lb-in.
DRX 100 > 50A = 6 Nm /53 lb-in.

**DRX 250 = 27174 (3P)
27175 (4P)
27194 (kit 60 pcs)**

CH 5

DRX 250 = 8 Nm /72 lb-in.
DRX 250 = 15 Nm /134 lb-in.

CH 5

DRX 250

Flexible	35 → 120 mm ² #2
or	250 MCM
Solid	35 → 150 mm ² #2
or	300 MCM

EQUIPMENT

4P

1P 2P 3P

SPARE PARTS

27181 (3P - 2 PCS)
27182 (4P - 3 PCS)

DRX 100 (1P) 27189

**DRX 100 (3P-4P) 27187
DRX 250 (3P-4P) 27188
DRX 100 (2P) 27190**

CLACK

DRX 100 (1P) 27189

**DRX 250 (3P-4P) 27188
DRX 100 (2P) 27190**

27180

**n° 3
ø5...ø8**

**DRX 100 27183 (3P) - 27184 (4P) - 27191 (2P)
DRX 250 27185 (3P) - 27186 (4P)**

1 Nm 8.8 lb-in

1 Nm 8.8 lb-in

CRACK

CRACK